LEVELO

AeroBoard Saffanio Leather

Wireless Keyboard

For iPad 11 / iPad 12.9"

SKU:LVLABK11BK-LVLABK129BK

Installation

1. Installation

Position the iPad on the magnetic stand as depicted.



2. Removal

Pull up the iPad to detach it from the stand.



3. Assembly

Insert the iPad into the case and fold the case to enhance portability.



Keyboard Instructions

Please read the operating instructions carefully before use .





Connection

Follow these steps to connect the device to your iPad.

1.Turn on the keyboard. Press and hold down the 🔗 key for three seconds, then wait for the keyboard pairing light to flash.



2.Navigate to the iPad Settings.



3.On your iPad, toggle the Bluetooth ON.



Bluetooth ON

4.Search for the device name "AeroBoard Keyboard" from the list of devices. The wireless signal light will turn off once pairing is successful.

Wireless Keyboard

Notice

The Bluetooth connection will automatically re-establish with your device upon the second usage.

Guide to Keyboard Key Combinations and Instructions (10.9"- 11")

Button Icon	Instruction	Button Icon	Instruction
fn ^ control + ~ esc	Fn+this key: Undo input	fn ^ control + ☼ ! 1	Fn+this key: Reduce brightness
fn ^ control + ☼ @ 2	Fn+this key: Increase brightness	fn ^ control + ⌨ # 3	Fn+this key: Virtual keyboard
fn ^ control + 🔍 $ 4	Fn+this key: Search	fn ^ control + 🎙 % 5	Fn+this key: Activate/deactivate Siri
fn ^ control + ◁◁ ^ 6	Fn+this key: Previous song	fn ^ control + ▷ǁ & 7	Fn+this key: Play/Pause
fn ^ control + ▷▷ * 8	Fn+this key: Next song	fn ^ control + 🔈 (9	Fn+this key: Mute
fn ^ control + 🔉) 0	Fn+this key: Volume down	fn ^ control + 🔊 — _	Fn+this key: Volume up
fn ^ control + ⌘ ☼ cmd	Fn+this key: Brightness adjustment	fn ^ control + ⌥ option	Fn+this key: Change the backlight color
🔗 + =	Long press to pair	🌐	Press to switch languages
fn ^ control	Combination key for fn+ control	ON/OFF	Power switch: Pull up: ON Pull down: OFF

Reset settings

To reset the keyboard, press and hold {[+ }] + |\ simultaneously for 3 seconds. The indicator will flash three times, signaling the keyboard pairing information is erased. The device will be restored to the second level of white backlight intensity.



Guide to Keyboard Key Combinations and Instructions (12.9")

Button Icon	Instruction	Button Icon	Instruction
esc	Undo input	☼	Reduce brightness level
☼	Increase brightness level	⊞	Access the recently opened windows
🔍	Search	🎙	Activate/deactivate Siri
◁◁	Previous song	▷‖	Play/Pause
▷▷	Next song	🔈	Mute
🔉	Volume down	🔊	Volume up
🔒	Lock screen	🔗	Long press to pair
🌐	Switch languages	⌘ ☼	Fn+this key: Brightness adjustment
⌥ ☼	Fn+this key: Change the backlight color	fn ^ control	Combination key for fn+ control
ON/OFF	Power switch: Pull up: ON Pull down: OFF		

Reset settings

To reset the keyboard, press and hold esc + ☼ + ☼ simultaneously for 3 seconds. The indicator will flash three times, signaling the keyboard pairing information is erased. The device will be restored to the second level of white backlight intensity.



Bluetooth Pairing and Indicator Guide

1. Power Indicator

The device is switched ON: The LED display lights up," 🔗 " flashes.
The device is switched OFF: The LED display is OFF and the keyboard stops working.

2. Bluetooth Connection Method

A. Upon switching ON, the device will automatically activate the pairing mode as the Bluetooth indicator " 🔗 " starts to flash.
B. For re-pairing, press and hold the " 🔗 " key for 3 seconds to activate the pairing mode, " 🔗 " flashes 3 times per second. The fast broadcast time is 180 seconds." 🔗 " turns OFF when pairing is successful. In case the pairing is not successful, the backlight and LED display will turn OFF, and the keyboard will enter sleep mode.

3. Reconnect Bluetooth Indicator

After the initial pairing is successful, switch the keyboard OFF and then ON again to automatically enter the Bluetooth reconnection mode. “ 🔗 ” flashes 3 times per second when entering the connection state. Upon establishing a successful connection within 5 seconds, the backlight, LED display, and “ 🔗 ” will remain ON. In case the pairing is not successful, the backlight and LED display will turn OFF, and the keyboard will enter sleep mode.

4. Charging Indicator ⚡

The ⚡ flashes during the charging process via the TYPE-C charging port. When fully charged, the charging indicator remains ON, and the battery display will read 100%.

5. Caps Lock Indicator

A. To type uppercase letters: Turn the caps lock feature ON.
B. To type lowercase letters: Turn the caps lock feature OFF.
C. To disable switching between languages using the Caps Lock key: Connect the device to your iPad. On your iPad, navigate to “Settings” → “General” → “Keyboard” → “Hardware Keyboard” → turn off “Switch Languages Using Caps Lock

6. Keyboard Sleep Mode

If the keyboard is either un-paired or not properly paired within 3 minutes of the pairing process, the backlight and display will turn off and the keyboard will enter sleep mode. The keyboard enters the standby state if not used within 30 seconds after the device is successfully paired. The keyboard enters sleep mode if not used for 10 minutes. To continue using the keyboard press any key on the keyboard. Note that touching the touchpad does not activate the keyboard from sleep mode. In case the battery level is below 15% (3.1-3.15V), the backlight will be turned OFF.

IPAD Trackpad Gestures Instructions

	**Tap**: Press with one finger until you feel a subtle click.		**Tap and hold**: Press and hold with one finger.
	**Drag**: Press and hold with one finger, then glide your finger across the trackpad.		**Open the Dock**: Swipe the pointer across the bottom edge of the screen using your fingertip.
	**Go to the Home Screen**: Swipe up with three fingers.		**Open Control Center**: Move the pointer with one finger to select the status icon on the upper right side. Tap on the icon. Alternatively, select the status icon in the upper right side, then swipe up with one finger.
	**Scroll up or down**: Swipe vertically up and down with two fingers.		**Scroll left or right**: Swipe horizontally with two fingers.
	Swipe downward with two fingers to open the search.		**Zoom**: Place two fingers together. Pinch to zoom in or spread them apart to zoom out.

 **Open the Today View**: When the Home or Lock screen is displayed, swipe right with two fingers.	 **Switch Between Open Apps**: Swipe left or right with three fingers.
 **Go to the Home Screen**: Swipe the pointer across the bottom of the pad with one finger. When the Dock appears, swipe the pointer across the bottom of the screen again. Alternatively, tap the bar at the bottom of the screen.	 **Open the App Switcher**: Swipe up with three fingers and briefly hold, then lift your finger. Alternatively, pinch with four fingers, hold for a moment, and then lift your fingers.

Notice

1. Operating System: iOS 15.0 and above (the equipment must support touch screens).

2. Touch Settings (After pairing successfully): Navigate to "Settings" → "General" → "Trackpad" → enable "Click / Double fingers assist point" (ON).

3. Sensitivity Settings: Go to "Settings" → "General" → "Trackpad" → adjust "Tracking Speed" to a comfortable level.

4. Auxiliary Touch Function:
4.1 Access "Settings" → "Auxiliary Function" → "Touch" → toggle "Auxiliary Touch" ON or OFF.
4.2 If the tablet has no mouse icon, perform the zoom in and out function by swiping double-fingers on the trackpad.

Specifications

Modulation	GFSK
Operating Voltage	3.0-4.2V
Operating Current (Backlight is OFF)	2.5mA
Standby Current	0.5mA
Sleeping Current	<0.04mA
Charging Current	200mA
Standby Time	≥2000 Hours
Charging Time	2.5 Hours
Operating Current for the Brightest Backlight	≈120mA
Continuous Operating Time for the Brightest Backlight	>4 Hours
Backlight Sleep Time	30s
Keyboard Deep Sleep Time	10min
Battery Capacity	500mAh
Continuous Operating Time (Backlight is OFF)	200 Hours

Caution

1. Please store and utilize the product at room temperature.

2. Do not disassemble, repair, or modify the product on your own.

3. Avoid exposing the product to rain or high humidity.

4. Do not use chemical solvents to clean the product.

5. Do not throw the product to prevent damage from falls.

6. If the product is not in use for an extended period, please recharge it every two months.

7. Do not dispose of the product carelessly or incinerate in high-temperature fire to prevent hazards.

FCC Statement

This device is in compliance with Part 15 of the FCC Rules. Its operation is contingent upon the following:
1. The device is not permitted to cause harmful interference.
2. The device must be receptive to any interference received, including that which may disrupt normal operation.
Unauthorized changes or modifications not specifically approved by the compliance authority could invalidate the user's right to operate this equipment.

Note: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules.

These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

1. Reorient or relocate the receiving antenna.
2. Increase the distance between the equipment and the receiver.
3. Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
4. Consult the dealer or an experienced radio/TV technician for help.

The device has been evaluated to meet general RF exposure requirements. It can be used in portable exposure conditions without restriction.

The content of this user manual and the specifications of this product are subject to change without prior notice.

Notice: Please read the user manual carefully to ensure correct operation of this product.

Warranty

Products that you buy directly from our Porodo website or shop come with a 24-month warranty.

When you buy Porodo products from any of our approved sellers, you only get a 12-month warranty. If you want to extend this warranty, go to our website at https://porodo.net/warranty and fill out the form with your information. Don't forget to upload a picture of the product too. After we've checked and accepted your request, we'll send you an email to confirm that your product's warranty has been extended.
For more info, please check:
porodo.net/warranty

Contact Us

If you have any questions about this Privacy Policy, please contact us at: info@porodo.net
Website: porodo.net
Service Support: support@porodo.net
Instagram: porodo